

THREE-PHASE HARMONIC FILTER $\rho=\%14$ $R_v=400V$ $F=50Hz$ $FR=134Hz$

PRODUCT CODE	Power (kVAr)	Current (A)	L (mH)	Connection	Dimensions (mm)			Mounting Size (mm)		Foot Installation	Weight (kg)	Loss Of Winding/W	Core Loss/W	Total Loss/W
					A	B	C	D	E					
BRH3 14/400/1	1	1,53	82,90	TERMINAL	150	150	72	100	55	M6	2,5	-	-	-
BRH3 14/400/1,5	1,5	2,39	53,15	TERMINAL	150	150	72	100	55	M6	4,5	-	-	-
BRH3 14/400/2,5	2,5	3,82	33,16	TERMINAL	180	175	85	125	60	M6	5	14,66	1,82	16,48
BRH3 14/400/3,12	3,12	4,77	26,57	TERMINAL	180	175	85	125	60	M8	6,5	16,43	4,08	20,51
BRH3 14/400/5	5	7,65	16,58	TERMINAL	180	175	115	125	90	M8	7,5	23,41	2,82	26,23
BRH3 14/400/6,25	6,25	9,56	13,26	TERMINAL	180	175	115	125	90	M8	8,5	17,16	1,46	18,62
BRH3 14/400/7,5	7,5	11,47	11,05	TERMINAL	240	225	100	175	75	M8	9	18,22	4,69	22,84
BRH3 14/400/10	10	15,30	8,29	TERMINAL	240	225	100	175	75	M8	11	19,45	5,85	25,3
BRH3 14/400/12,5	12,5	19,12	6,63	TERMINAL	240	225	100	175	75	M8	13,5	23,22	6,89	30,11
BRH3 14/400/15	15	22,95	5,53	TERMINAL	240	225	110	175	85	M8	14	26,28	9,13	35,41
BRH3 14/400/20	20	30,6	4,15	BUSBAR	270	240	135	200	110	M8	20,5	36,54	8,28	44,82
BRH3 14/400/25	25	38,25	3,32	BUSBAR	270	240	150	200	125	M8	22	45,68	10,35	56,03
BRH3 14/400/30	30	45,9	2,76	BUSBAR	295	255	165	200	130	M8	31	51,74	18,42	70,16
BRH3 14/400/40	40	61,2	2,07	BUSBAR	295	255	170	200	135	M8	35	59,89	24,67	84,56
BRH3 14/400/50	50	76,5	1,66	BUSBAR	300	255	180	200	145	M8	41	63,62	24,67	88,29
BRH3 14/400/60	60	91,8	1,38	BUSBAR	355	310	190	250	155	M8	44	76,08	11,04	87,12
BRH3 14/400/75	75	119	1,1	BUSBAR	355	310	210	250	175	M10	72	81,03	19,07	100,1
BRH3 14/400/100	100	159	0,82	BUSBAR	400	360	210	250	175	M10	85	92,36	28,41	120,77

