

**MONOPHASE HARMONIC FILTER  $p=\%5,67$   $R_v=230V$   $F=50Hz$   $FR=210Hz$** 

PRODUCT CODE	Power (kVAr)	Current (A)	Connection	Dimensions (mm)			Mounting Size (mm)		Foot Installation	Weight (kg)	Loss Of Winding/W	Core Loss/W	Total Loss/W
				A	B	C	D	E					
BRH1 5,67/230/0,5	0,5	2,60	TERMINAL	84	70	60	70	45	M5	1,35	-	-	-
BRH1 5,67/230/1	1	5,21	TERMINAL	84	70	80	70	65	M5	1,95	9,42	1,54	10,96
BRH1 5,67/230/1,5	1,5	7,82	TERMINAL	84	70	80	70	65	M5	2,45	13,67	2,48	16,15
BRH1 5,67/230/2,5	2,5	13,04	TERMINAL	96	80	96	80	80	M5	3,8	17,55	2,58	20,13
BRH1 5,67/230/5	5	26,08	BAR(M6)	120	100	98	100	80	M5	6,35	24,12	6,63	30,75
BRH1 5,67/230/7,5	7,5	39,13	BAR(M8)	120	100	120	100	100	M8	8,3	39,87	12,56	52,43
BRH1 5,67/230/10	10	52,17	BAR(M8)	150	125	128	125	100	M8	11,3	47,05	28,74	75,79

**MONOPHASE HARMONIC FILTER  $p=\%7$   $R_v=230V$   $F=50Hz$   $FR=189Hz$** 

PRODUCT CODE	Power (kVAr)	Current (A)	L (mH)	Connection	Dimensions (mm)			Mounting Size (mm)		Foot Installation	Weight (kg)	Loss Of Winding/W	Core Loss/W	Total Loss/W
					A	B	C	D	E					
BRH1 7/230/0,5	0,5	2,47	25,34	TERMINAL	84	70	60	70	45	M4	1,3	-	-	-
BRH1 7/230/1	1	4,95	12,67	TERMINAL	84	70	80	70	65	M5	1,5	16,74	5,7	22,44
BRH1 7/230/1,5	1,5	7,43	8,45	TERMINAL	84	70	80	70	65	M6	2,5	13,81	7,74	21,55
BRH1 7/230/2,5	2,5	12,38	5,07	TERMINAL	96	80	96	8	80	M6	4	22,42	14,99	37,41
BRH1 7/230/5	5	24,77	2,53	BAR(M6)	120	100	98	100	80	M8	6,5	36,28	18,81	55,09
BRH1 7/230/7,5	7,5	37,16	1,69	BAR(M8)	120	100	120	100	100	M8	8,5	42,05	43,06	85,11
BRH1 7/230/10	10	49,15	1,28	BAR(M8)	150	125	110	120	80	M8	11,5	65,31	15,55	80,86

